

**EXIT FIXTURE RETROFIT KIT (MODEL: GFXTE-3)  
120 VAC 2.2W WATTS (EACH) MAXIMUM  
(CONFORMS TO UL924)**

**SAVE THESE INSTRUCTIONS**

**IMPORTANT SAFEGUARDS-READ AND FOLLOW ALL SAFETY  
INSTRUCTIONS**

When installing electrical equipment, safety precautions should always be followed including the following:

- 1) Do not use outdoors.
- 2) Do not use this equipment for other than the intended use.
- 3) Servicing of this equipment should be by qualified personnel only.
- 4) Do not mount near gas or electric heaters.
- 5) Use on 120 volt circuits only.

**INSTALLATION INSTRUCTIONS FOR  
INTERMEDIATE, CANDELABRA OR BAYONET BASES  
LED SCREW-IN EXIT FIXTURE RETROFIT KIT.**

- 1) Remove face(s) of existing exit fixture with red pane(s) and remove existing incandescent lamps.
- 2) Replace lamps with the proper LED unit (intermediate, candelabra or bayonet type base).
- 3) Screw in LED unit until they are illuminated (finger tight).
- 4) Position LED unit so that the widest part of the unit is facing the letters "EXIT" (Turn counterclockwise until parallel with the fixture face).
- 5) Replace the exit sign face (s) and red panel (s).

**IMPORTANT: LED'S** must be parallel to the face of the exit fixture to insure proper light distribution.

**CAUTION:**

For use only with six inch single or double-faced, stencil-faced fixtures with white or black interiors.

For use in exit lights with interior enclosure dimensions of 6-1/4" H X 9-1/2" W X 7/8" D minimum and 8-7/8" H X 13-7/16" W X 3-1/4" D maximum, including all obstructions.

Not for use in:

- Exit fixtures with an exit legend larger than 6 inches.
- Exit fixtures employing more than two incandescent lamps larger than 20 watts each.
- Edge-Lite or Fluorescent fixtures.